

# ATEM 1 M/E Advanced Panel 30



The ATEM 1 M/E Advanced Panel 30 features a single M/E row, 30 input button design that is ideal for switching big productions from desk surfaces that are not deep enough for a bigger panel. It has 3 independent system control LCDs plus it can control up to 4 M/Es in larger switchers. All input buttons include LCDs for custom labeling and it also includes an independent select bus! Dual power inputs provide redundancy and the built-in 4 port Ethernet switch means no additional network equipment is needed so it will fit even the most challenging live production spaces!

US\$6,155

## Connections

#### Ethernet

4 x 10/100/1000 BASE-T with loop output for additional control panels or computers.

#### **Software Updates** 1 x USB-C for firmware updates.

## **Product Specifics**

Number of Mix Effects Rows	Preview Transition	<b>Dedicated Macro Buttons</b> 1 x 30
<b>Direct Cross Points</b>	<b>Transition Rate Displays</b>	<b>Transport Control Buttons</b>
30	Via main menu	8
Shifted Cross Points	<b>LCD Menu Displays</b>	<b>Destination Bus</b>
60	3	1

Fader Bar	3 Axis Joystick	Numeric Keypad
1	1	1

Software

Software Applications

ATEM Software Control Panel.

# **Operating Systems**





Mac 13.0 Ventura, Mac 14.0 Sonoma or later.

# Power Requirements

Input Voltage	Redundant Power	Power Usage
2 x Internal 100 - 240V AC.	Yes	80W

Physical Specifications



#### **Environmental Specifications**

**Operating Temperature** 0° to 40° C (32° to 104° F) **Storage Temperature** -20° to 60° C (-4° to 140° F) **Relative Humidity** 0% to 95% non-condensing

# What's Included

ATEM 1 M/E Advanced Panel 30 Welcome wallet with QR code for software download

Warranty

12 Month Limited Manufacturer's Warranty.

All items on this website are copyright Blackmagic Design Pty. Ltd. 2024, all rights reserved. All trademarks are property of their respective owners. MSRP includes local import taxes. Excludes local VAT and local shipping costs. This website uses remarketing services to advertise on third party websites to previous visitors to our site. You can opt out at any time by changing cookie settings. <u>Privacy Policy</u>

Blackmagic Design Authorized Reseller